

Release Notes

BL652

Version 28.10.7.0

February 2020

Release notes are a summary of new and enhanced features, resolved issues, and known issues that are not resolved in this firmware version. This release note describes the changes and enhancements to the firmware of the BL652 *smartBASIC* based Bluetooth Low Energy Module in reverse chronological order.

For each version (excluding the initial 28.6.1.2) there are subsections for 'New Features', 'Bug Fixes' and 'Known Issues'.

BL652 firmware version numbers consist of four numbers in the format **W.X.Y.Z** which can be read back from the module by submitting the command AT I 3 when it is in command mode.

W signifies the module ID, which in the case of BL652 is 28.

X is used to indicate the underlying BLE stack version and so far, the values are:

6	Production release of Nordic's Softdevice version 3.0.0
7	Production release of Nordic's Softdevice version 5.0.0
8	Production release of Nordic's Softdevice version 5.1.0
9	Production release of Nordic's Softdevice version 6.1.0
10	Production release of Nordic's Softdevice version 7.0.1

Y is the release version, i.e. the major build number

Z is a sub-build number. When it is 0 or an even number it signifies that the firmware image is a production image that has been fully regression tested. An odd number indicates an engineering image.

VERSION 28.10.7.0 (FEBRUARY 2020)

This firmware is built to work with v7.0.1 of the S132 Softdevice from Nordic Semiconductor which is BT Spec version 5.1 qualified.

New Features

The following are new features in the current version, please refer to the manual for usage.

- **smartBASIC:**
 - Capability to send and receive adverts up to 255 bytes long on any PHY.
 - Added new extended adverts functions as follows:-
 - BleAdvSetCreate()
 - BleAdvSetNewData()
 - BleAdvSetStart()
 - BleAdvSetStop()
 - BleScanStartEx()
 - BleExtRptMetadata()
 - BleConnectExtended()
 - BleExtAdvRptAppendAD()
 - BleExtAdvRptAddUuid16()
 - BleExtAdvRptAddUuid128()
 - BleExtAdvRptGetSpace()
 - Added the following new events related to extended adverts (see user guide for details):-

- EVBLE_EXTADV_END
- EVBLE_EXTADV_RPT
- EVBLE_EXTSCN_RPT
- EVBLE_EXTADV_RPT_INCOMPLETE
- While scanning a whitelist can be specified
- It is now possible to initiate a 2MPHY connection via extended adverts
- Added new function to use static pass key :- BlePairingStaticPasskey()
- Added new new config key 217 to specify max advert sets. Currently limited to just 1.
- Added new new config key 218 to specify reserved max time for packet transmissions in a connection interval
- Up to 28KByte of RAM is now available for smartBASIC use instead of just 20Kbyte
- Softdevice now allocated 0x9000 bytes instead of 0xB000
- When scanning is aborted due to a connection initiation, event EVBLE_SCAN_ABORTED is sent to the application.
- Added AT I 2085 and 2086 which returns status of BLE stack startup
- Added SYSINFO(2085) and SYSINFO(2086) which returns status of BLE stack startup

Changes

- The File System is now 82K instead of 64K to accommodate large apps with debug prints.

Resolved Issues

The following issues have been resolved in this release:

- Fix to internal helper function that walks an advert report to check if an AD element already exists.
- Intermittent high current usage after floating point operation now fixed
- Memory leak fixed when scanning and then a connection is initiated because scanning is aborted.
- Function EccCalcSharedSecret() now validates that input parameters are the right length.
- Bug Fix: One byte SPI read was producing 16 clock cycles instead of 8
- Bug Fix: Arithmetic overflow when a timeout greater than 2²⁴ was specified
- AT I 2024 and SYSINFO(2024) return correct values for negative celcius temperatures

VERSION 28.9.6.0 (NOVEMBER 2018)

This firmware is built to work with v6.1.0 of the S132 Softdevice from Nordic Semiconductor which is BT Spec version 5.0 qualified.

New Features

The following are new features in the current version; please refer to the manual for usage.

- **ESB:** Added Nordic's proprietary Enhanced ShockBurst (ESB) protocol.
- **BLE:** Added ability to set channel map from smartBASIC application.
- Added utilities for extracting firmware + filesystem hex and ufw files.
- nRFx-Command-Line-Tools updated to version 9.8.1.

Changes

- **VSP:** VSP via indicate feature is no longer supported.

Resolved Issues

The following issues have been resolved in this release:

- **VSP:** Fixed a bug where data may be dropped when built-in VSP is used and ATT_MTU is increased (12784).

Known Issues

The following are known issues in this release:

- During a BLE connection, when a GATT service is changed in a GATT server, the GATT client does not receive an event notifying it of the change (9628).
- For the GATT server, the long writes feature on authorizable characters is not yet implemented and will be added in future releases (11193).

VERSION 28.9.5.0 (SEPTEMBER 2018)

This firmware is built to work with v6.1.0 of the S132 Softdevice from Nordic Semiconductor which is BT Spec version 5.0 qualified.

New Features

The following are new features in the current version; please refer to the manual for usage.

- **LESC:** Added fix for Bluetooth vulnerability VU#304725 where public keys weren't validated during LESC pairing.
- **BLE:** Added the ability to advertise and perform a connection over 2MPHY modulation.
- **Watchdog:** Exposed watchdog timer functionality through smartBASIC API.
- Moved to Softdevice v6.1.0 and SDK15.0.0.

Resolved Issues

The following issues have been resolved in this release:

- **SPI** – Fixed bug where SPI operation would hang if the bus is not correctly configured (13287).

Known Issues

The following are known issues in this release:

- During a BLE connection, when a GATT service is changed in a GATT server, the GATT client does not receive an event notifying it of the change (9628).
- For the GATT server, the long writes feature on authorizable characters is not yet implemented and will be added in future releases (11193).

VERSION 28.8.4.0 (JUNE 2018)

This firmware is built to work with v5.1.0 of the S132 Softdevice from Nordic Semiconductor which is BT Spec version 5.0 qualified.

New Features

The following are new features in the current version; please refer to the manual for usage.

- **FLOAT:** Added the ability to declare and use float type variables and float functionality.
- **VSP:** Added the ability to configure the hardware VSP device name.
- **SPI Slave:** Added SPI Slave API to allow the BL652 to operate as an SPI Slave peripheral.
- Moved to softdevice v5.1.0 and SDK v14.2.0.

Resolved Issues

The following issues have been resolved in this release:

- Bluetooth connection with BT5 phones (e.g. iPhone X, Samsung Galaxy S8) no longer fails when using hardware VSP (12637 & 12647).
- UART no longer locks up when two devices exchange data at different baud rates (9688).
- Fixed GPIO power consumption rise after GPIO is used as a frequency output (12531).
- RTS no longer asserts too soon after power up or reset (9625).

Known Issues

The following are known issues in this release:

- During a BLE connection, when a GATT service is changed in a GATT server, the GATT client does not receive an event notifying it of the change (9628).
- For the GATT server, the long writes feature on authorizable characters is not yet implemented and will be added in future releases (11193).

VERSION 28.7.3.0 (OCTOBER 2017)

This firmware is built to work with v5.0.0 of the S132 Softdevice from Nordic Semiconductor which is BT Spec version 5.0 qualified.

New Features

The following are new features in the current version; please refer to the manual for usage.

- **2M PHY:** added the Bluetooth 5 feature to switch to the higher 2M PHY modulation.
- **BLE Connections:** Increased number of outgoing connections (central links) from 7 to 8.
- **Cryptography:** Added cryptographic functions for generating public/private keypair and computing shared key.
- **Authentication:** Added function for generating authenticated hash using supplied data and key.
- **Filesystem:** increased the filesystem size for smartBASIC applications from 48K to 64K.
- **Security:** Added to the ability to enable readback protection.
- Moved to softdevice v5.0.0 and SDK v14.

Changes

The following changes have occurred to this version of the firmware.

- **L2CAP:** L2CAP functionality has been removed from the firmware and new API will be added in future releases.
- **BleMaxPacketLengthSet:** The function BleMaxPacketLengthSet has been replaced with the config key 216. To set the maximum packet length, the command 'AT+CFG 216 nNewMaxPacketLength' should be issued followed by a reset (e.g. using 'ATZ') for the new value to take effect.

Resolved Issues

The following issues have been resolved in this release:

- Using SPI open with an invalid flag now returns the correct error response.
- The CTS and RTS pins can now be used as normal GPIO pins when the UART is opened with no handshaking.
- Connecting to certain Samsung Android devices can cause an NRF_FAULT.

Known Issues

The following are known issues in this release:

- During a BLE connection, when a GATT service is changed in a GATT server, the GATT client does not receive an event notifying it of the change (9628).

- For the GATT server, the long writes feature on authorizable characters is not yet implemented and will be added in future releases (11193).
- RTS is asserted too soon after on power up on reset. To overcome this, wait 200ms after CTS is asserted before sending data via the UART (9625).

VERSION 28.6.2.0 (MAY 2017)

This firmware is built to work with v3.0.0 of the S132 Softdevice from Nordic Semiconductor which is BT Spec version 4.2 qualified.

New Features

The following are new features in the current version; please refer to the manual for usage.

- **LE Ping:** added the ability to use authenticated payload timeout to monitor the integrity of an encrypted link.
- **Bandwidth Configuration:** Added the option to achieve high bandwidth on first connection. This allows up to six packets to be sent per connection interval, therefore improving the BLE throughput.
- **Data in notifications and write events:** Added new events that allow BLE data to be thrown in the events therefore significantly enhancing the throughput.
- **BleVspInfo:** The length of the VSP Rx/Tx characteristics can now be returned using BleVspInfo(5).
- **Gatt Server Write:** added a new function that allows the user to write data at a certain offset.

Resolved Issues

The following issues have been resolved in this release:

- The unexpected behavior of UartWrite() at 921600 baud rate has now been resolved (10415).
- When a characteristic that requires authentication is written to using 'write without response' procedure, an event is now thrown to the application (EVAUTHVALEX) allowing the user to choose to accept or reject the data (11050).
- Added EVBLE_PASSKEY event so that during passkey pairing, the connection handle is included as part of the event, therefore enabling the application to identify the device performing the pairing (11145).
- Added a function to get the maximum packet length supported by the device - BleMaxPacketLengthGet (10599).
- If slave prefers LESC pairing and master only supports legacy, the pairing fails instead of reverting back to legacy pairing (11164).

Known Issues

The following are known issues in this release:

- During a BLE connection, when a GATT service is changed in a GATT server, the GATT client does not receive an event notifying it of the change (9628).
- For the GATT server, the long writes feature on authorizable characters is not yet implemented and will be added in future releases (11193).
- When two devices are bonded, erasing the bond on one device can sometimes cause a disconnection (9663).

VERSION 28.6.1.4 (DECEMBER 2016)

This firmware is built to work with v3.0.0 of the S132 Softdevice from Nordic Semiconductor which is BT Spec version 4.2 compliant.

New Features

The following are new features in the current version; please refer to the manual for usage.

- **Packet Length Extension:** added the ability to set the maximum packet length up to 251 bytes.
- **Attribute MTU:** Added the ability to increase the maximum transmission unit for attributes, i.e. allowing GATT operations to be performed on attributes larger than 20 bytes.
- **Maximum Attribute Length:** added ability to increase the attribute data size up to 244 bytes.
- **Long Writes:** added support for Long Writes on both the GATT client and the GATT server.

Resolved Issues

The following issues have been resolved in this release:

- The central device can now get an event with the connection parameter update request from the peripheral instead of being forced into accepting the peripheral's parameters.
- The Device Information service now contains the BL652 device name instead of the BL600.

Known Issues

The following are known issues in this release:

- During a BLE connection, when a GATT service is changed in a GATT server, the GATT client does not receive an event notifying it of the change (9628).
- Unexpected behavior occurs with the UartWrite() function at 921600 baud rate when writing large amounts of data, causing data loss. As a work around the PRINT smartBASIC function can be used instead (10415).
- BleMaxPacketLengthGet() is not implemented and will be added in future releases when the softdevice supports it. If BleMaxPacketLengthSet() succeeds then that value can be saved in the smartBASIC application and used as a reference for the maximum packet length (10599).
- For the GATT server, the long writes feature on authorizable characters is not yet implemented and will be added in future releases (11193).
- When two devices are bonded, erasing the bond on one device can sometimes cause a disconnection (9663).

VERSION 28.6.1.2 (AUGUST 2016)

This firmware is built to work with v3.0.0 of the S132 Softdevice from Nordic Semiconductor which is BT Spec version 4.2 compliant.

Known Issues

The following are known issues in this release:

- During a BLE connection, when a GATT service is changed in a GATT server, the GATT client does not receive an event notifying it of the change (9628).
- When adding the Device Information service to a GATT table using BleSvcRegDevInfo(), the Firmware Revision String contains the value BL600:v28.6.1.2 when it should be BL652:v28.6.1.2.

Further Information

Further information relating to the BL652 and its firmware is available from the Laird website at <http://www.lairdtech.com/products/bl652-ble-module>